



Product Code

F02438

VDS LIGHT/BUZZER ACTIVATOR

Reference

2438

EAN

8424299024387

Description.

Description

Necessary to activate an external device (courtesy light, second door, etc) from the corresponding button (additional button) located in the phone or monitor.

Small size allows installation in electrical cabinets. Can be flush-fit in standard boxes 10x10 cm. With adhesive strips for fixing, or may be screwed directly onto the wall.

VDS system:

Simplified installation audio and video door entry system that does not use house call wires. The call is made by transmission of a digital call code generated by the VDS amplifier.

- In new works, installation can be carried out with the following type of wiring: UTP CAT5 / 5 wire / 3 wire + Coaxial (video).

Lets you manage up to 199 homes, 2 entrance accesses and a central guard unit.

Maximum distance from first access to last home: 200 m.

- In replacement works, the change from analogue entry to video entry system can be done taking advantage of the existing wiring.

The system capacity and distance will depend on the installation wiring.

VDS amplifier comes with voice synthesizer as standard issue.

When the door release is activated a message is heard: "The door is open, please close the door behind you".

The home terminals require simple programming done from the outdoor panel. By means of this programming a call code is assigned to each terminal (telephone or monitor).

Communication is private.

Wiring. Audio: 3-wire bus. Video: UTP CAT5 / 5 wire / 3 wire + Coaxial (video).

Maximum distance from first access to last home: 200 m.

Technical Details

Dimensions: 62x70x20 mm (height-width-depth).

Power supply: 18 Vdc

Details.

Weight (kg)	Packaging measurements	Video Door Entry system
0.071	(height x width x depth) cm	Technologie
	6,3x2,4x9	VDS

Manuals

- 94525 Activador de Luces VDS-DUOX Ref 2438 V11_16.pdf

Declaration of conformity

- DOCF02438EN.pdf