



Product Code

F29001

TIMER

Reference	EAN
29001	8424299290010

## Description.

### Description

The timer has the following connections and controls: - PDT relay to activate the external device (C, No, Nc). - Potentiometers to adjust the activation time: Minute adjusted potentiometer (P1) and Second adjusted potentiometer (P2). - Timed Activation Button Connection (S,-): activates the timer relay during the programmed time. - Button connection for Reset (R,-); Allows the timer to be deactivated before the programmed time has elapsed. - Direct Activation Button Connection (Ab,-): activates the timer relay when the button connected here is pressed. - Connection for call activation (I1, I2): allows the calling wire and the negative from the outdoor panel be connected (4+N systems) and activate the time when making a call.

### Technical Details

- Power supply: 9~14 Vac ;11~18 Vdc - Consumption: With 12 Vdc power supply: 20 mA standby, 50 mA active. With 12 Vac power supply: 50 mA standby, 110 mA active. - Maximum output values: Power (resistive load): 1250VA or 150W Voltage (resistive load): 125 Vdc, 380 Vac. - Maximum Temperature: 0~+65°C - Timing: P1: between 0 and 6 minutes approximately. P2: between 1 and 60 seconds approximately. - Call Activation: Electronic Call: 4Vpp~18Vpp. Backup Call: 4Vac~12Vac.

## Details.

Weight (kg)	Packaging measurements	Video Door Entry system
0.073	(height x width x depth) cm	Technologie
	9x6,5x2,5	GENERICA

## Manuals

- 94918b Temporizador  
Ref 29001 V08\_08.pdf

## Declaration of conformity

- DOCF29001EN.pdf