



Product Code

F08053

UNIVERSAL LIGHT COMMANDER

Reference

8053

EAN

8424299080536

Description.

Description

Necessary to activate an external device (courtesy light, second door, etc) from the corresponding button (additional button) located in the phone or monitor.

Small size allows installation in electrical cabinets. Can be flush-fit in standard boxes 10x10 cm. With adhesive strips for fixing, or may be screwed directly onto the wall.

Conventional System: uses wires common to the whole installation plus 1 call wire (or call return) per home..

Recommended in small to medium-sized buildings (up to 50 residents approx), with several accesses and central guard unit. For residential complexes with general entrance and interior blocks.

Wiring:

- Audio door entry system: 4 common wires + N (1 call wire per home).
- Video door entry system: 7 common wires + 1 video coaxial+N (1 call wire per home).

Maximum distance in the installation based on the cable section used (see technical manuals).

Technical Details

Dimensions: 62x70x20 mm (height-width-depth).

Power supply:

- Audio: 12 Vac
- Video: 18 Vdc

Details.

Weight (kg)	Packaging measurements	Video Door Entry system
0.0634	(height x width x depth) cm	Technologie
	6,3x2,4x9	GENERICA

Manuals

- 94460 Activador de Luces
Ref 8053 V02_02.pdf

Declaration of conformity

- DOCF08053ES.pdf