

Product Code

F09446

DUOX PLUS VEO WIFI 4.3" MONITOR



Reference

9446

EAN

8424299094465

Description.

Description

VEO WIFI is equipped with a Wi-Fi connection that allows calls forwarding to mobile devices. Thanks to the Fermax DuoxMe app, available free of charge on Play Store and App Store, the functions of the video doorphone can be managed from a smartphone or a tablet, in order to connect you to your home, wherever you are. The DUOX VEO WIFI monitor is made of high-impact ABS plastic. It incorporates a 4,3" (16:9) panoramic color TFT screen. Its unique handset design incorporating a magnet enables the user to put it back into position correctly when the call is finished. Its balanced design of pure lines is distinguishing, modern and minimal.

Technical Details

GENERAL CHARACTERISTICS

- Technology: DUOX PLUS (non-polarised 2 wire full digital system)
- Audio/Video system: Audio/Video Color
- Set-up (Installation): Surface mounted (order connector ref. 9447 separately)
- Desktop support: Yes (ref. 9410)

- Handset with magnet to facilitate the hang up: Yes
- Induction loop available: Yes (replace handset with ref. 3443 or order monitor ref. 9455 which already includes the induction loop))
- Screen dimensions: 4,3" (Panoramic 16:9)
- Screen resolution (H x V): 480 x 272
- Color of the product: Matt white
- Number of pushbuttons: 4
- Kind of pushbuttons: Mechanical (silicone)
- Number of leds for lighted indications: 1 (red with 3 states: always ON, slow/fast blinking)

PROGRAMMING OF THE TERMINAL ADDRESS

- From the terminal: From the OSD menu
- From the outdoor panel or guard unit: Yes
- From the outdoor panel throughout the apartment door bell: Yes

FEATURES

- Automatic picture capture when the visitor calls (PHOTOCALLER): Yes (1 photo/call, until 150 photos, 368 x 288 pixels). This feature can be enabled by the user. Disabled by default.
- Guard unit call: Yes (by means of the door release button)
- Auto-on: Yes (with 3 outdoor panels/cameras)
- OSD menu: Yes
- Additional function F1: Yes (Button F1 sends a negative and/or command)
- Additional function F2: Yes (it only sends command, no negative)
- Apartment door bell differentiated from the outdoor panel: Yes
- Connection for additional devices (call extension, light/buzzer activator, etc.): Yes (ref. 2040, ref. 2438, ref. 3267)
- Additional terminals on the same address: Yes, max. 2 additional terminals (additional power supply can be required)
- Doormatic (automatic door release for offices, etc.): No

ADJUSTMENTS

- Date and time: Yes
- Ring tones selection: Yes (5). Configurable for Block Panel 0, Block Panel 1, General Entrance Panel 0 and Concierge unit.
- Call volume control: Yes (10 levels by OSD menu)
- Do-not-disturb mode: Yes (by OSD menu) + Red led indication
- Audio volume control: Yes (10 levels by OSD menu)
- Brightness, color and contrast control: Yes (by OSD menu)

TECHNICAL FEATURES

- Product dimensions (width x height x depth) mm: 200 x 200 x 23 (44 including handset)
- Time to answer or open the door since the call is done: 30 s.

- Conversation time: 90 s.
- Conversation privacy: Yes
- Voltage: 18-24 Vdc
- Maximum consumption: 5.6 W
- Standby consumption (paired and connected): 1.3 W
- Working temperature (°C, °F); Humidity: [-5°C, +40°C][23°F, 104°F]; [0%, 90%]
- Line adaptor included in the terminal: Yes (A, C, default position OFF)
- Connections: Bin, Bin, Bout, Bout, -, A+, F1, T

CALL FORWARDING (APP "DuoxMe" FOR SMARTPHONES & TABLETS)

- Call forwarding to smartphones and tablets: Yes
- Connectivity: Wifi (2,4 Ghz)

Details.

Product measurements (height x width x depth) mm	Product height (mm)	Product width (mm)	Product depth (mm)
200x200x44	200	200	44

Weight (kg)	Packaging measurements (height x width x depth) cm	Video Door Entry system Technologie
0.5457	5,1x22,2x20,7	DUOX

Manuals

- 970166Ah Monitor VEO wifi duox plus V12_24.pdf
- 970166Eh Monitor VEO wifi duox plus V12_24.pdf
- 970166Fh Monitor VEO wifi duox plus V12_24.pdf
- 970166g Monitor VEO wifi duox plus V10_22.pdf
- 970166lh Monitor VEO wifi duox plus V12_24.pdf
- 970166Ph Monitor VEO wifi duox plus V12_24.pdf
- https://d7rh5s3nxmpy4.cloudfront.net/CMP2008/files/970167g%20Guia%20rap%20monitor%20VEO%20wifi%20duox%20plus%20V12_24.pdf, ,

Declaration of conformity

- [DOCF09446EN.pdf](#)

Accessories



F09447

DUOX PLUS CONNECTOR



F03389

UNIVERSAL FRAME LARGE



F09410

VEO MONITOR DESKTOP SUPPORT



F03443

VEO TELEPHONE HANDSET
W/INDUCT.LOOP

Training video

- <https://youtube.com/playlist?list=PLf1YNFmssC37H-1CN64lo6ND28rmVsQit>