

Product Code

F09459

## DUOX PLUS VEO-XS WIFI DDA 4.3" MONITOR



Reference

9459

EAN

8424299094595

### Description.

---

#### Description

Hands-free DUOX VEO-XS WIFI monitor is characterised by its small size and extra-flat thickness. Thanks to its OSD menu and the layout of the buttons, interaction with the user is simple and intuitive. Made of high impact ABS plastic. Texturised finish for easy cleaning and ultraviolet protection. VEO-XS WIFI incorporates a 4,3" (16:9) panoramic color TFT screen. Its balanced design of pure lines is distinguishing, modern and minimal. VEO-XS WIFI is equipped with a Wi-Fi connection that allows calls forwarding to mobile devices. Thanks to the Fermax BLUE app, available free of charge on Play Store and App Store, the functions of the video doorphone can be managed from a smartphone or a tablet, in order to connect you to your home, wherever you are.

#### Technical Details

##### GENERAL CHARACTERISTICS

- Technology: DUOX PLUS (non-polarised 2 wire full digital system)
- Audio/Video system: Audio/Video Color
- Set-up (Installation): Surface mounted (order connector ref. 9447 separately)

- Desktop support: Yes (ref. 9420)
- Hands-free communication: Yes
- Press-to-talk communication configurable: Yes
- Induction loop: Yes
- Screen dimensions: 4,3" (Panoramic 16:9)
- Screen resolution (H x V): 480 x 272
- Color of the product: Matt white
- Number of pushbuttons: 5
- Kind of pushbuttons: Mechanical (silicone)
- Number of leds for lighted indications: 3 (red, blue, green with different states)

### PROGRAMMING OF THE TERMINAL ADDRESS

- From the terminal: From the OSD menu
- From the outdoor panel or guard unit: Yes
- From the outdoor panel throughout the apartment door bell: Yes

### FEATURES

- Automatic picture capture when the visitor calls (PHOTOCALLER): Yes (1 photo/call, until 150 photos, 368 x 288 pixels). This feature can be enabled by the user. Disabled by default.
- Guard unit call: Yes (by means of the door release button)
- Auto-on: Yes (with 3 outdoor panels/cameras)
- OSD menu: Yes
- Additional function F1: Yes (Button F1 sends a negative and/or command)
- Additional function F2: Yes (it only sends command, no negative)
- Apartment door bell differentiated from the outdoor panel: Yes
- Connection for additional devices (call extension, light/buzzer activator, etc.): Yes (ref. 2040, ref. 2438, ref. 3267)
- Additional terminals on the same address: Yes, max. 2 additional terminals (additional power supply can be required)
- Doormatic (automatic door release for offices, etc.): Yes (configurable until 12h). Green Led ON.

### ADJUSTMENTS

- Date and time: Yes
- Ring tones selection: Yes (5). Configurable for Block Panel 0, Block Panel 1, General Entrance Panel 0 and Concierge unit.
- Call volume control: Yes (10 levels by OSD menu)
- Do-not-disturb mode: Yes (by OSD menu) + Red led indication
- Audio volume control: Yes (10 levels by OSD menu)
- Brightness, color and contrast control: Yes (by OSD menu)

### TECHNICAL FEATURES

- Product dimensions (width x height x depth) mm: 125 x 165 x 21

- Time to answer or open the door since the call is done: 30 s.
- Conversation time: 90 s.
- Conversation privacy: Yes
- Voltage: 18-24 Vdc
- Maximum consumption: 6.9 W (14.4W if the induction loop is activated)
- Standby consumption (paired and connected): 1.3 W
- Working temperature (°C, °F); Humidity: [-5°C, +40°C][23°F, 104°F]; [0%, 90%]
- Line adaptor included in the terminal: Yes (A, C, default position OFF)
- Connections: Bin, Bin, Bout, Bout, -, A+, F1, T

### CALL FORWARDING (APP "BLUE" FOR SMARTPHONES & TABLETS)

- Call forwarding to smartphones and tablets: Yes (App Compatible with iOS>=11; Android>=6)
- Connectivity: Wifi (2,4 Ghz) and 3G/4G
- Pairing of the monitor with the wifi router of the house: Once the App is installed, the user must register first. Pairing by scanning a QR code in the monitor menu.
- Maximum number of apartments that can be managed from the App: No limit
- Maximum number of smartphones/tablets where call divert from the same house can be used: 10 (including administrator's and invited user's devices)
- Maximum number of users that can be invited by the administrator: 5
- Calls reception: Audio and Video from outdoor panels/concierge units. With pre-view before audio communication is on.
- Conversation time: 90 s.
- Mute: Yes
- Video off: To reduce the data consumption when being in 4G mode
- Switching of outdoor panels/cameras: Yes. It allows for switching to other panels/cameras (if any) with the same sequence than the monitors.
- Auto-on: Yes. communication possible with 3 outdoor panels/cameras without being called
- Activate additional feature (stairlight relay, second door, etc.): Yes. F1 button.
- Door opening: Yes, protected by the unblocking code of the smartphone/tablet: PIN, fingerprint, pattern or face ID.
- Concierge call: Yes
- Calls register: Yes (answered calls in green; missed calls in red)
- Settings: Name and picture of the house; Do not disturb; Change password; Ringtone and vibration mode.
- Picture & Video capture: Not from the APP. Only automatically from the monitor
- Available languages: 16 (Spanish, English, French, German, Portuguese, Finnish, Czech, Polish, Dutch, Norwegian, Greek, Danish, Swedish, Hebrew, Russian, Arabic)

## Details.

---

Product measurements (height x width x depth) mm	Weight (kg)	Packaging measurements (height x width x depth) cm	Video Door Entry system Technologie
165 x 125 x 21	0.2987	17x12,8x4	DUOX

### Manuals

- 970164Elg Monitor VEO XS wifi duox plus V10\_23.pdf
- 970164FAg Monitor VEO XS wifi duox plus V10\_23.pdf
- 970164Pg Monitor VEO XS wifi duox plus V10\_23.pdf
- 970165d\_Guia\_rap\_monitor\_VEO\_XS\_wifi\_duox\_V10\_23.pdf
- 970283E\_Manual\_app\_Blue\_V12\_22.pdf
- 970283I\_Manual\_app\_Blue\_V12\_22.pdf

### Accessories



F09447  
DUOX PLUS CONNECTOR



F03388  
UNIVERSAL FRAME



F03389  
UNIVERSAL FRAME LARGE



F09420  
VEO-XS/VEO-XL MONITOR DESKTOP SUPPORT

### Training video

- <https://youtube.com/playlist?list=PLf1YNFmssC37H-1CN64lo6ND28rmVsQit>