

Product Code

F14833

WIT 10' HOME AUT. MONITOR POE BLACK MEET

Reference

14833

EAN

8424299148335

Description.

Description

WIT is a capacitive touch screen monitor available in 7" and 10" versions. WIT graphical interface provides an intuitive user experience since it is design focused on a residential intercom use. FEATURES • Capacitive Touch Screen (7" / 10") • Hands Free Audio Communication • High definition colour TFT • Different ringtones depending on call source • 3 Different colour options (white, black, gold) • Remote firmware upgrade • Android based • Available in 8 languages (English, Spanish, German, Polish, Russian, Hebrew, Turkish, Chinese) • Door bell connection with IP camera visualization • IP CCTV visualization (up to 8) • Aux IP CCTV camera visualization and aux relay operation during call (up to 4) • Relay activation (up to 8 using relay module) • Home Automation Ready through Apps (in 7" and 10") • Automatic and Manual Picture Capture • Integrated 7 zones alarm + tamper FUNCTIONS 1. CONCIERGE Users can call the desired concierge by selecting it on the list shown in the user interface. If the concierge has a camera attached a video communication will be established, otherwise only audio. 2. PANEL AND CCTV CAMERA AUTO ON Users can open the panel's video channel of their respective block for surveillance purpose. This can be done by selecting the panel the user wants to supervise or the CCTV camera to visualize. Once the panel communication is established, the user can take pictures, talk and open the door if wanted. 3. AUX CAMERA AND AUX DOOR LOCK RELEASE DURING CONVERSATION When a call is received from the panel, it is possible to display different aux cameras (up to 4) to get a different angle of view or to follow the visitor. At the same time different aux relays (up to 4) can be activated to open additional gates or barriers. 4. VIDEO DOOR BELL It is possible to connect a pushbutton to the monitor so it will trigger the doorbell sound on the monitor. The door bell call can automatically display the video coming from an IP CCTV camera, increasing the security. 5. HOME TO HOME CALL The monitor allows the users to call different apartments within the same community. 6. CALL LOG Users can have a clear view of their call history in the CALL LOG interface and are able to browse through the pictures taken for each call. 7. PHOTO CAPTURE When receiving a call, it is possible to capture automatically a photo. It is possible to take additional photos if desired. 8. MESSAGES Users can receive text messages from their property management so they can easily know if there is a package, a maintenance schedule or an import event on their community (software management required). Maximum 64 messages. 9. LIFT CONTROL Tenants can enable the lift to their visitors to access their floor at the same time the panel door lock is opened from the monitor. Tenants can call the lift before leaving their

apartment, so the lift car is ready on the floor. 10. ALARMS The monitor provides 7 alarm zones management, managed under 3 simple modes: HOME: Lowest Security level. SLEEP: Medium Security level. OUT: Highest Security level. 11. SOS User generates an SOS alarm by touching this icon several seconds, sending a message to the concierge and management software. 12. DO NOT DISTURB It is possible to set the monitor to DO NOT DISTURB mode, so the calls will not produce any sound during a defined period of time. Do not disturb led will light up if this function is active. REFERENCES WIT 7 14701 WIT 7 MONITOR POE WHITE 14703 WIT 7 MONITOR POE BLACK 14704 WIT 7 MONITOR POE GOLD 9541 WIT / MIO CONNECTOR WIT 10 14811 WIT 10 HOME AUT. MONITOR POE WHITE 14813 WIT 10 HOME AUT. MONITOR POE BLACK 14814 WIT 10 HOME AUT. MONITOR POE GOLD 1489 WIT 10" WALL FLUSH BOX

Details.

Product measurements (height x width x depth) mm	Weight (kg)	Packaging measurements (height x width x depth) cm	Video Door Entry system
270 x 168 x 20	1.0639	6,8x31x21,5	Technologie MEET

Manuals

- 970295_Guia_Rap_Inst_Monitor_WIT_V07_23.pdf


Declaration of conformity

- DOCF14813EN.pdf

Accessories



F95411
NEO/WIT MONITOR
CONNECTOR MEET



F01489
WIT 10" MONITOR FLUSH BOX MEET