


Product Code

F49171

# 1W DUOX PLUS MEMOV CITY VEO-XL WIFI KIT



Reference

49171

EAN

8424299491714

## Description.

### Description

Fermax presents the VEO-XL WIFI DUOX PLUS kits **for single-family houses, offices and businesses** .

The kits include all the necessary materials for installation: CITYLINE entrance panel with Memokey keyboard, VEO-XL WIFI monitor and power supply.

In addition, they work with DUOX PLUS, a fully digital door entry and video door entry system and technology on two non-polarized wires, which simplifies their installation while maintaining the highest quality in the product and design,

They include the VEO-XL WIFI DUOX PLUS monitor as standard, equipped with a Wi-Fi connection that **allows calls to be forwarded to mobile devices** .

Thanks to the **Fermax BLUE application** , available for free in the Play Store and App Store, the video door entry functions can be managed directly from a mobile or tablet, to connect to your home, wherever you are. By connecting your WiFi DUOX PLUS monitors with the BLUE app, a range of possibilities will open up. Of all of them we highlight two that will be key: Divert calls from the video door entry unit to your mobile and open the door to the house from a distance.

They also come as a standard with the **Photocaller** function , which automatically captures an image of the caller. If the user decides to activate this function, the monitor stores up to 150 images, indicating the date and time when they were taken. When the maximum capacity has been reached, taking a new photo will erase the first one stored. The screen always indicates if there are photos not displayed or if the date / time are not configured.

The **VEO-XL WIFI DUOX PLUS** hands-free **monitor** is characterized by its small size and thickness, extra-flat. Thanks to its OSD menu and the layout of the buttons, its interaction with the user is simple and intuitive.

It is made of high impact ABS plastic.

Includes a 7" widescreen color display (16: 9).

Its balanced design of pure lines is distinctive, modern and minimalist.

The board includes an integrated Memokey keyboard for opening the door from the keyboard by entering a PIN code (up to 100 codes, 100 users).

**DUOX PLUS is the new digital technology** that exceeds all expectations. Because it makes the difficult easy.

#### Technical Details

Includes:

- 73881 MEMOVISION DUOX PLUS 1/L plate. S5:130x246.
- 8855 S5 built-in box: 115x233x45.
- 9469 VEO-XL WIFI DUOX PLUS 7" Monitor.
- 9447 DUOX PLUS connector
- 4825 Power supply+filter 24VDC-2.5A DIN10
- 4802 12Vac/1A Power Supply. DIN4

Video:

- Sensor: 1/3" color CMOS.
- Camera 480p (SD), 720x480
- Minimum external lighting: 0 lux. Since it has LEDs, no additional lighting is required.
- S/N >45dB.
- Frame rate 25 fps.
- 7" monitor resolution: 800x480
- Video Codec: H264 Highline Profile
- Auto iris.
- Auto BLC.
- Viewing angle 100° horizontal, 80° vertical.
- Fisheye correction.
- Color night vision through white LEDs.
- Pan & Tilt digital zoom.

## Details.

Weight (kg)  
3.098425

Packaging measurements  
(height x width x depth) cm  
26x24x15

Video Door Entry system  
Technologie  
DUOX

Access Control Technology  
TECLADO

### Manuals

- 970198c GR Kit Vid DUOX Plus VEO XL WiFi V05\_24.pdf
- 97572 Memokey NCity 100 codigos A5 V03\_10.pdf

### Products included



F08855  
CITY FLUSH BOX S5



F09447  
DUOX PLUS CONNECTOR



F09469  
DUOX PLUS VEO-XL WIFI 7" MONITOR



F04802  
P.S.U. DIN4 230VAC/12VAC-1A



F04825  
POWER SUPP. UNIT+FILTER DIN10  
24VDC-2.5A



F73881  
1W DUOX PLUS MEMOVISION CITY  
PANEL

### Accessories



F08855  
CITY FLUSH BOX S5



F09195  
CITY PANEL S5 MODULAR  
DECORATIVE FRAME



F08382  
CITY SINGLE ANGLE BOX S5



F08404  
CITY SINGLE HOOD S5



F07065  
CITY SURFACE BOX S5



F08255  
CITYLINE DECORATIVE FRAME S5



F03267  
DUOX PLUS RELAY



F02040  
ELECTRONIC EXTENSION CALL



F09454  
IP/DUOX PLUS CAMERA INTERFACE



F03389  
UNIVERSAL FRAME LARGE



F02438  
VDS LIGHT/BUZZER ACTIVATOR



F09420  
VEO-XS/VEO-XL MONITOR DESKTOP  
SUPPORT