



Product Code F94411 1W DUOX PLUS VIDEO CITY VEO-WIFI KIT

Reference 94411

EAN 8424299944111

## Description.

### Description

Fermax presents the new VEO WIFI DUOX PLUS kits for single-family houses, offices and businesses .

The kits include all the necessary materials for its installation: CITYLINE entrance panel, VEO WIFI monitor and power supply.

In addition, they work with DUOX PLUS, a fully digital door entry and video door entry system and technology on two non-polarized wires, which simplifies their installation while maintaining the highest quality in the product and design,

They include the VEO WIFI DUOX PLUS monitor as standard, equipped with a Wi-Fi connection that **allows calls to be forwarded to mobile devices**.

Thanks to the **Fermax BLUE application**, available for free in the Play Store and App Store, the video door entry functions can be managed directly from a mobile or tablet, to connect to your home, wherever you are. By connecting your WiFi DUOX PLUS monitors with the BLUE app, a range of possibilities will open up. Of all of them we highlight two that will be key: Divert calls from the video door entry unit to your mobile and open the door to the house from a distance.

They also come as a standard with the **Photocaller** feature, which automatically captures an image of the caller. If the user decides to activate this function, the monitor stores up to 150 images, indicating the date and time when they were taken. When the maximum capacity has been reached, taking a new photo will erase the first one stored. The screen always indicates if there are photos not displayed or if the date / time are not configured.

The VEO WIFI DUOX PLUS monitor is made of high impact ABS plastic.

Includes a 4.3 "widescreen color display (16: 9).

The unique and exclusive design of the handset incorporates a magnet that makes it easy for the user to position it, ensuring a correct hanging at the end of the conversation.

Its balanced design of pure lines is distinctive, modern and minimalist.





DUOX PLUS is the new digital technology that exceeds all expectations. Because it makes the difficult easy.

#### Technical Details

It includes:

- 40708 CITY PANEL DUOX PLUS S1 CP101
- 8948 CITY FLUSH BOX FOR KIT (S1)
- 9446 DUOX VEO WIFI 4.3" MONITOR
- 9447 DUOX VEO/VEO-XS CONNECTOR
- 4825 POWER SUPP. UNIT+FILTER DIN10 24VDC-2.5A
- 4802 P.S.U. DIN4 230VAC/12VAC-1A

### Video:

- Sensor: 1/3 "CMOS color.
- Effective pixels> 340K. (the camera captures 720x480)
- Minimum external lighting: 0 lux. Since it has LEDs, no additional lighting is required.
- S / N> 45dB.
- Frame rate 25 fps.
- Resolution> 368x288 pixels.
- Video codec: H264 Highline Profile
- Auto iris.
- Auto BLC.
- Angle of vision 100° horizontal, 80° vertical.
- Fish eye correction.
- Color night vision through white LEDs.
- Pan & Tilt digital zoom.

# Details.

200x200x44 23x24x	
width x depth) mm 2.468366 (height	x width x depth) cm
Product measurements (height x Weight (kg) Packagi	ing measurements

#### Manuals

- 970173c GR Kit Vid DUOX PLUS VEO WIFI V08\_20.pdf
- 970264b Adaptaciones kits Duox Plus V01\_24.pdf

Video Door Entry system
Technologie
DUOX



Declaration of conformity

• DOCF94411EN.pdf

Products included



F08948 CITY FLUSH BOX FOR KIT (S1)



F04802 P.S.U. DIN4 230VAC/12VAC-1A



F40708 CITY PANEL DUOX PLUS S1 CP101



F04825 POWER SUPP. UNIT+FILTER DIN10 24VDC-2.5A



DUOX PLUS CONNECTOR



F09446 DUOX PLUS VEO WIFI 4.3" MONITOR

## Accessories



F08851 CITY FLUSH BOX S1



CITY SINGLE HOOD S1



F09191 CITY PANEL S1 MODULAR DECORATIVE FRAME

CITYLINE DECORATIVE FRAME S1



CITY S1 SURFACE BOX

F09444

DUOX PLUS CAMERA INTERFACE

Si 🖛

GERLENNS \*\*\*



F07061



F08378

CITY SINGLE ANGLE BOX S1

DUOX PLUS RELAY







F02040 
 ELECTRONIC EXTENSION CALL
 UNIVERSAL FRAME LARGE
 VDS LIGHT/BUZZER ACTIVATOR
 VEO MONITOR DESKTOP SUPPORT

F03389

F02438

F09410



VEO TELEPHONE HANDSET W/INDUCT.LOOP