



Product Code

F94421

2W DUOX PLUS VIDEO CITY VEO WIFI KIT

Reference

94421

EAN

8424299944210

Description.

Description

Fermax presents the new **VEO WIFI DUOX PLUS** kits for single-family houses, offices and businesses .

The kits include all the necessary materials for its installation: CITYLINE entrance panel, VEO WIFI monitor and power supply.

In addition, they work with DUOX PLUS, a fully digital door entry and video door entry system and technology on two non-polarized wires, which simplifies their installation while maintaining the highest quality in the product and design,

They include the VEO WIFI DUOX PLUS monitor as standard, equipped with a Wi-Fi connection that allows calls to be forwarded to mobile devices .

Thanks to the Fermax DuoxMe application , available for free in the Play Store and App Store, the video door entry functions can be managed directly from a mobile or tablet, to connect to your home, wherever you are. By connecting your WiFi DUOX PLUS monitors with the DuoxMe app, a range of possibilities will open up. Of all of them we highlight two that will be key: Divert calls from the video door entry unit to your mobile and open the door to the house from a distance.

They also come as a standard with the Photocaller feature, which automatically captures an image of the caller. If the user decides to activate this function, the monitor stores up to 150 images, indicating the date and time when they were taken. When the maximum capacity has been reached, taking a new photo will erase the first one stored. The screen always indicates if there are photos not displayed or if the date / time are not configured.

The VEO WIFI DUOX PLUS monitor is made of high impact ABS plastic.

Includes a 4.3" widescreen color display (16: 9).

The unique and exclusive design of the handset incorporates a magnet that makes it easy for the user to position it, ensuring a correct hanging at the end of the conversation.

Its balanced design of pure lines is distinctive, modern and minimalist.

DUOX PLUS is the new digital technology that exceeds all expectations. Because it makes the difficult easy.

Technical Details

Includes:

- 40008 CITY DUOX PLUS 2/L plate. S1: 130x128
- 8948 S1 built-in box: 115x114x45
- 9446 VEO DUOX PLUS WIFI Monitor 4.3" (x2)
- 9447 DUOX PLUS connector (x2)
- 4826 Power supp. unit+filter DIN6 24VDC-1.5A
- 4802 Power supply DIN4 230VAC/12VAC-1A
- 3255 DUOX PLUS line adapter

Video:

- Sensor: 1/3" color CMOS.
- Effective pixels > 340K. (camera captures 720x480)
- Minimum external lighting: 0 lux. Since it has LEDs, no additional lighting is required.
- S/N >45dB.
- Frame rate 25 fps.
- Resolution > 368x288 pixels.
- Video Codec: H264 Highline Profile
- Auto iris.
- Auto BLC.
- Viewing angle 120° horizontal, 80° vertical.
- Fisheye correction.
- Color night vision through white LEDs.
- Pan & Tilt digital zoom.

Details.

Weight (kg)	Packaging measurements	Video Door Entry system
3.048299	(height x width x depth) cm	Technologie
	23x23,7x18,2	DUOX

Manuals

- 970048b_Config_VOZ_Placas_Puls_VIDEO_DUOX_Plus_V07_22.pdf

- 970338 Guia rapida kits DUOX PLUS unificada V12_24.pdf

Products included



F08948

CITY FLUSH BOX FOR KIT (S1)



F40008

CITY PANEL DUOX PLUS S1 CP201



F09447

DUOX PLUS CONNECTOR



F03255

DUOX PLUS LINE ADAPTOR



F09446

DUOX PLUS VEO WIFI 4.3" MONITOR



F04802

P.S.U. DIN4 230VAC/12VAC-1A



F04826

POWER SUPP. UNIT+FILTER DIN6
24VDC-1.5A

Accessories



F08851

CITY FLUSH BOX S1



F09191

CITY PANEL S1 MODULAR
DECORATIVE FRAME



F07061

CITY S1 SURFACE BOX



F08378

CITY SINGLE ANGLE BOX S1



F08400

CITY SINGLE HOOD S1



F08251

CITYLINE DECORATIVE FRAME S1



F09444

DUOX PLUS CAMERA INTERFACE



F03267

DUOX PLUS RELAY



F02040

ELECTRONIC EXTENSION CALL



F03389

UNIVERSAL FRAME LARGE



F02438

VDS LIGHT/BUZZER ACTIVATOR



F09410

VEO MONITOR DESKTOP SUPPORT



F03443

VEO TELEPHONE HANDSET
W/INDUCT.LOOP