



Product Code

FE02532

MDS DIRECT CITYMAX GUARD UNIT

Reference

2532

EAN

8424299025322

Description.

Description

The new CityMax guard unit has a 4" screen, dialling keypad (located under the phone handset) and fast access function buttons for easy and convenient facility and guard unit management.

Extra flat format, made in high impact ABS plastic and with a mirror polish type finish for easy cleaning.
Includes desktop support. Allows surface installation.

Basically, the Central Guard Unit acts as "filter" between the visitors to a building and its residents. During normal operation, the calls made from any outdoor access panel to the building are received in the Central Guard Unit, which can announce the visit to the corresponding resident, pass on the call, or deal with it personally. The guard unit, through its built-in display, informs on all incidents and actions in the facility: call source, call type, call in progress, calls waiting, latest communication, etc. The guard unit has several operating modes. The guard unit can communicate with any access (outdoor panel) or home.

MDS Direct system: Simplified BUS installation digital audio and video door entry system that lets you manage large buildings and average sized residential complexes.

Recommended for.

- Individual buildings:

Up to 99 homes and 5 accesses (between audio and video panels) and 1 central guard unit.

Up to 99 homes and 9 accesses (between audio and video panels) if there is no central guard unit.

- In residential complexes:

- MDS Direct interior block combined with MDS Digital or Direct general entrances: Up to 99 interior blocks of 99 homes with a maximum of 9 accesses per block.
- MDS Direct MDS City or ADS interior block combined with MDS Direct general entrances: Up to 5 general entrances and 1 central guard unit or 9 general entrances without guard unit.

No Central Guard Unit required. Includes access control by keypad.

MDS systems require floor Decoders to connect the homes to the installation BUS and act as insulators. Home-panel communication is private.

Wiring:

- Audio: 6-wire bus.

- Video: audio bus + Coaxial (video) + 2 power supply wires.

Maximum distance in the installation depending on the cable section used (see technical manuals).

Technical Details

Search keys: Let you look for the name of the resident you wish to call.

Call key (bell): To call house phones or other guard units.

Details.

Weight (kg)	Packaging measurements (height x width x depth) cm	Video Door Entry system Technologie
2.0954	24,5x28,8x26	MDS

Manuals

- 94870b Manual de usuario CC MDS DIRECT Ref 2532
V02_10.pdf
- 94873c Manual de instalacion CC MDS DIRECT Ref 2532
V02_10.pdf

Declaration of conformity

- DOCFE02532EN.pdf